



Sample Valve Part Number:

437EC-3FBF75-D

MODEL SPECIFICATION	
PART CODE	DESCRIPTION
43	MANIFOLD

MOTOR SPECIFICATIONS		
PART CODE	SWITCH	DESCRIPTION
E	DPDT	22 RPM, 0.6 SECOND SHUTOFF VALVE
EC	SPST	

MOTOR CABLES	
PART CODE	DESCRIPTION
D	POSITIVELY SWITCHED w/ DIN CONNECTOR
DN	NEGATIVELY SWITCHED w/ DIN CONNECTOR

MANIFOLD SIZES	
PART CODE	DESCRIPTION
1	1-VALVE MANIFOLD
3	3-VALVE MANIFOLD
5	5-VALVE MANIFOLD
7	7-VALVE MANIFOLD
9	9-VALVE MANIFOLD

VALVE TYPE	
PART CODE	DESCRIPTION
2	2-WAY VALVE
3FB	FLOW BACK
3	3-WAY VALVE

INLET TYPE	
PART CODE	DESCRIPTION
BLANK	LARGE QUICK CONNECT
F75	75-SERIES FLANGE

Other manifold sizes are available.

Mini-DIN Cable Assembly Part Code Example:

58480EC-15-VX

CABLE WIRE CODE	
PART CODE	DESCRIPTION
E	2 WIRE CABLE
EC	3 WIRE CABLE

LENGTH SPECIFICATION	
PART CODE	DESCRIPTION
05	0.5 METER (20")
15	1.5 METER (60")
30	3.0 METER (120")

WIRING CONNECTORS	
PART CODE	DESCRIPTION
VX	FIRST NUMBER REFERS TO CONNECTOR CODE. SECOND NUMBER REFERS TO WIRING CODE.

For "E" style motors use 2-wire cable.
For "EC" style motors use 3-wire cable.

See page 105 for electrical connectors and codes.